**Question: What is the menu layout for the alien and alienPro DVRs?**

**Answer: See pages 1-3 for alienDVR, 4-6 for the alien Pro range.**

## Alien DSD105 quick help guide. (operations menu)

| FUNCTION | PAGE | PRIME MENU | SECONDARY MENU | FUNCTION |
|---|---|---|---|---|
| SWITCH OFF PASSWORD | 29 | DISPLAY | | PUT X IN REQUIRE PASSWORD BOX<br>CONFIRM DISPLAY |
| DATE/TIME | 29 | DISPLAY THEN SETUP | | ENTER TO SAVE<br>CONFIRM DISPLAY |
| PLAYBACK | 20 | PRESS PLAY BUTTON | | ENTER CHANNEL<br>ENTER REC TYPE<br>ENTER TIME REQ<br>CLICK SEARCH<br>USE UP/DOWN ARROW BUTTONS TO SELECT<br>PRESS PLAY |
| BACKUP | 22 | PRESS PLAY BUTTON AFTER INSTALLING BACKUP MEDIA | | ENTER CHANNEL<br>ENTER REC TYPE<br>ENTER TIME REQ<br>CLICK SEARCH<br>USE UP/DOWN ARROW BUTTONS TO SELECT<br>PRESS BACKUP |
| MOTION DETECTION | 35 | CAMERA | AREA | SET MOTION DET LEVEL<br>0 = LOW 5 = HIGH<br>PRESS CONFIRM<br>PRESS PTZ TO SELECT ALL OR PRESS A TO CLEAR ALL<br>PRESS EDIT & TO SETUP AREAS USE ARROW KEYS<br>PRESS SAVE THEN CONFIRM AREA<br>CONFIRM CAMERA |
| PREVIEW/SEQUENCING | 37 | DISPLAY SELECT PREVIEW SETUP | PREVIEW | SWITCH 1 – 4 CHANNEL<br>SELECT SEQUENCING<br>CONFIRM PREVIEW<br>CONFIRM DISPLAY |

This CCTV installation tip is aimed at helping you to install CCTV equipment. If you are looking for answers on "how to fit CCTV" or perhaps "how to network a DVR or NVR" or even "how to get CCTV on your mobile phone" why not check out our full range of CCTV installation tips at: **www.systemq.com**

*How to guides aim to answer commonly asked questions in a concise and informative manner. They are for advice & guidance only and do not replace any of the manuals or other literature supplied with our products.*

System Q Ltd. McGregor's Way, Turnoaks Business Park, Hasland, Chesterfield, S40 2WB
Telephone: **01246 200 000** Website: **www.systemq.com** Email: **support@systemq.com**

Copyright © System Q ltd

| | | | | |
|---|---|---|---|---|
| RECORDING SETUP | 38<br><br><br><br><br><br><br><br>39 | RECORDING<br><br>RECORDING CHANNEL CONFIG | <br><br><br><br><br><br><br>SCHEDULE | <br>HD FULL OVERWRITE<br><br>CIF/QCIF<br><br>FRAME RATE<br><br>ENABLE REC<br><br>SET SCHEDULE<br>CONFIRM SCHEDULE<br>CONFIRM RECORD |
| AUDIO | 38<br><br>37/38 | RECORDING<br><br>DISPLAY & SELECT PREVIEW SETUP | <br><br>PREVIEW | SET STREAM TYPE TO AUDIO&VIDEO<br>CONFIRM RECORD<br><br>SET AUDIO BY TICKING AUDIO PREVIEW<br>CONFIRM PREVIEW |
| NETWORK PARAMS | 45 | NETWORK | | SET IP, PORT, SUBNET MASK, GATEWAY, HTTP PORT.<br>CONFIRM NETWORK |
| PTZ<br><br><br><br>CONNECT RS485<br><br>PTZ PRESETS<br><br><br><br><br><br><br><br>TOUR SETUP<br><br><br><br>RUN TOUR<br><br><br><br>PATTERN SETUP<br><br><br><br><br><br><br><br>RUN PATTERN | 47<br><br><br><br>7<br><br>47/48<br><br><br><br><br><br><br><br>47/48<br><br><br><br>47/48<br><br><br><br>47/48<br><br><br><br><br><br><br><br>47/48 | PTZ<br><br><br><br>T+ T-<br><br>PTZ SET PRESETS SELECT PRESET SETUP<br><br><br><br><br><br><br><br>PTZ SEQUENCE NO: SETUP<br><br><br><br>PTZ SEQUENCE NO: SETUP<br><br><br><br>PTZ CRUISE SETUP<br><br><br><br><br><br><br><br>PTZ CRUISE SETUP | <br><br><br><br><br><br><br><br>SET PRESET<br><br><br><br><br><br><br><br>SEQUENCE<br><br><br><br>SEQUENCE<br><br><br><br>SET CRUISE PRESS REC CRU<br><br><br><br><br><br><br><br>SET CRUISE PRESS START CRU | SET CHANNEL, BAUD RATE, PROTOCOL, ADDR.<br>CONFIRM PTZ<br><br>CONNECT A LINE + TO T+ & B LINE – TO T-<br><br><br><br><br><br><br><br>SET PRESET POINTS<br>CONFIRM SET PRESET<br>CONFIRM PTZ<br><br><br><br>CREATE TOUR<br>CONFIRM SEQUENCE<br>CONFIRM PTZ<br><br>ENTER TOUR NUMBER (SEQUENCE)<br>STARTSEQ/STOP<br>RETURN<br><br><br><br>ENTER PTZ CONTROL & USE KEYS TO CREATE PATTERN, THEN PRESS ENTER TO SAVE PATTERN<br>RETURN<br>CONFIRM PTZ<br><br>RETURN |

This CCTV installation tip is aimed at helping you to install CCTV equipment. If you are looking for answers on "how to fit CCTV" or perhaps "how to network a DVR or NVR" or even "how to get CCTV on your mobile phone" why not check out our full range of CCTV installation tips at: **www.systemq.com**

***How to guides aim to answer commonly asked questions in a concise and informative manner. They are for advice & guidance only and do not replace any of the manuals or other literature supplied with our products.***

System Q Ltd. McGregor's Way, Turnoaks Business Park, Hasland, Chesterfield, S40 2WB
Telephone: **01246 200 000** Website: **www.systemq.com** Email: **support@systemq.com**

Copyright © System Q ltd

| | | | | |
|---|---|---|---|---|
| UTILITIES | 50 | UTILITIES | DEFAULT<br><br>HARD DISK MANAGE<br><br>REBOOT<br><br>POWER OFF<br><br>VIEW LOG<br><br>SYSTEM INFO | PRESS RESTORE<br><br>HDD INFO & FORMAT<br><br>REBOOT<br><br>POWER OFF<br><br>VIEW LOG<br><br>SYSTEM INFO |
| USERNAME, PASSWORD & RIGHTS | 25/29 | PRESS MENU | | PASSWORD CHANGES<br>LOCAL RIGHTS<br>REMOTE RIGHTS |
| VGA & VIDEO MODE | 29 | DISPLAY | VIDEO STANDARD<br><br>VGA RESOLUT. | SET TO PAL MODE<br><br>SELECT RESOLUTION<br><br>CONFIRM |
| CANCEL BEEP SOUND | 9 | PRESS MENU FOR >5 SECS | | DISABLES BEEPER |

This CCTV installation tip is aimed at helping you to install CCTV equipment. If you are looking for answers on "how to fit CCTV" or perhaps "how to network a DVR or NVR" or even "how to get CCTV on your mobile phone" why not check out our full range of CCTV installation tips at: **www.systemq.com**

***How to guides aim to answer commonly asked questions in a concise and informative manner. They are for advice & guidance only and do not replace any of the manuals or other literature supplied with our products.***

System Q Ltd. McGregor's Way, Turnoaks Business Park, Hasland, Chesterfield, S40 2WB
Telephone: **01246 200 000** Website: **www.systemq.com** Email: **support@systemq.com**

Copyright © System Q ltd

# Alien DSD500 range quick help guide (operations manual)

| FUNCTION | PAGE | PRIME MENU | SECONDARY MENU | FUNCTION |
|---|---|---|---|---|
| SWITCH OFF PASSWORD | | DISPLAY | | PUT X IN REQUIRE PASSWORD BOX<br>CONFIRM DISPLAY |
| DATE/TIME<br><br>DST (Daylight Saving Time) | 40/41 | DISPLAY THEN D/TIME<br><br>D/TIME SETUP | D/TIME<br><br>D/TIME | CONFIRM TO SAVE<br>CONFIRM DISPLAY<br><br>TICK DST & TIME ZONES<br>CONFIRM TO SAVE<br>CONFIRM DISPLAY |
| PLAYBACK | 29 | PRESS PLAY BUTTON<br><br>ENTER USER & PASSWORD<br>PRESS EDIT | | ENTER CHANNEL<br>ENTER REC TYPE<br>ENTER TIME REQ<br>CLICK SEARCH<br>USE UP/DOWN ARROW BUTTONS TO SELECT<br>PRESS PLAY |
| BACKUP | 31 | PRESS PLAY BUTTON AFTER INSTALLING BACKUP MEDIA | | ENTER CHANNEL<br>ENTER REC TYPE<br>ENTER TIME REQ<br>CLICK SEARCH<br>USE UP/DOWN ARROW BUTTONS TO SELECT<br>PRESS BACKUP |
| MOTION DETECTION | 46 | CAMERA | AREA | SET MOTION DET LEVEL<br>0 = LOW 5 = HIGH<br>PRESS CONFIRM<br>PRESS PTZ TO SELECT ALL OR PRESS A TO CLEAR ALL<br>PRESS EDIT & TO SETUP AREAS USE ARROW KEYS<br>PRESS SAVE THEN CONFIRM AREA<br>CONFIRM CAMERA |
| PREVIEW/SEQUENCING | 49 | DISPLAY SELECT PREVIEW SETUP | PREVIEW | SWITCH 1 – 4 CHANNEL<br>SELECT SEQUENCING<br>CONFIRM PREVIEW<br>CONFIRM DISPLAY |
| RECORDING SETUP | 49<br><br>49 | RECORDING<br><br>RECORDING CHANNEL CONFIG | <br><br>SCHEDULE | HD FULL OVERWRITE<br><br>QCIF/CIF/2CIF/DCIF/4CIF<br><br>FRAME RATE<br><br>ENABLE REC<br><br>SET SCHEDULE<br>CONFIRM SCHEDULE<br>CONFIRM RECORD |

This CCTV installation tip is aimed at helping you to install CCTV equipment. If you are looking for answers on "how to fit CCTV" or perhaps "how to network a DVR or NVR" or even "how to get CCTV on your mobile phone" why not check out our full range of CCTV installation tips at: **www.systemq.com**

***How to guides aim to answer commonly asked questions in a concise and informative manner. They are for advice & guidance only and do not replace any of the manuals or other literature supplied with our products.***

System Q Ltd. McGregor's Way, Turnoaks Business Park, Hasland, Chesterfield, S40 2WB
Telephone: **01246 200 000** Website: **www.systemq.com** Email: **support@systemq.com**

Copyright © System Q ltd

| | | | | |
|---|---|---|---|---|
| AUDIO | 49<br><br>49 | RECORDING<br><br>DISPLAY & SELECT PREVIEW SETUP | <br><br>PREVIEW | SET STREAM TYPE TO AUDIO&VIDEO<br>CONFIRM RECORD<br><br>SET AUDIO BY TICKING AUDIO PREVIEW<br>CONFIRM PREVIEW<br>CONFIRM DISPLAY |
| NETWORK PARAMS | 55 | NETWORK | | SET IP, PORT, SUBNET MASK, GATEWAY, HTTP PORT.<br>CONFIRM NETWORK |
| PTZ<br><br>CONNECT RS485<br><br>PTZ PRESETS<br><br>TOUR SETUP<br><br>RUN TOUR<br><br>PATTERN SETUP<br><br>RUN PATTERN | 57/58<br><br>13/14<br><br>58<br><br>58/59<br><br>59<br><br>58/59<br><br>59 | PTZ<br><br>T+ T-<br><br>PTZ SET PRESETS SELECT PRESET SETUP<br><br>PTZ SEQUENCE NO: SETUP<br><br>PTZ SEQUENCE NO: SETUP<br><br>PTZ CRUISE SETUP<br><br>PTZ CRUISE SETUP | <br><br><br><br>SET PRESET<br><br>SEQUENCE<br><br>SEQUENCE<br><br>SET CRUISE PRESS REC CRU<br><br>SET CRUISE PRESS START CRU | SET CHANNEL, BAUD RATE, PROTOCOL, ADDR.<br>CONFIRM PTZ<br><br>CONNECT A LINE + TO T+ & B LINE – TO T-<br><br>SET PRESET POINTS<br>CONFIRM SET PRESET<br>CONFIRM PTZ<br><br>CREATE TOUR<br>CONFIRM SEQUENCE<br>CONFIRM PTZ<br><br>ENTER TOUR NUMBER (SEQUENCE)<br>STARTSEQ/STOP<br>RETURN<br><br>ENTER PTZ CONTROL & USE KEYS TO CREATE PATTERN, THEN PRESS ENTER TO SAVE PATTERN<br>RETURN<br>CONFIRM PTZ<br><br>RETURN |
| UTILITIES | 60/62 | UTILITIES | DEFAULT<br><br>HARD DISK MANAGE<br><br>REBOOT<br><br>POWER OFF<br><br>VIEW LOG<br><br>SYSTEM INFO | PRESS RESTORE<br><br>HDD INFO & FORMAT<br><br>REBOOT<br><br>POWER OFF<br><br>VIEW LOG<br><br>SYSTEM INFO |
| USERNAME, PASSWORD & RIGHTS | 36/39 | PRESS MENU | | PASSWORD CHANGES<br>LOCAL RIGHTS<br>REMOTE RIGHTS |

This CCTV installation tip is aimed at helping you to install CCTV equipment. If you are looking for answers on "how to fit CCTV" or perhaps "how to network a DVR or NVR" or even "how to get CCTV on your mobile phone" why not check out our full range of CCTV installation tips at: **www.systemq.com**

***How to guides aim to answer commonly asked questions in a concise and informative manner. They are for advice & guidance only and do not replace any of the manuals or other literature supplied with our products.***

System Q Ltd. McGregor's Way, Turnoaks Business Park, Hasland, Chesterfield, S40 2WB
Telephone: **01246 200 000** Website: **www.systemq.com** Email: **support@systemq.com**

Copyright © System Q ltd

| | | | | |
|---|---|---|---|---|
| VGA & VIDEO MODE | 40 | DISPLAY | VIDEO STANDARD<br><br>VGA RESOLUT. | SET TO PAL MODE<br><br>SELECT RESOLUTION CONFIRM |
| CANCEL BEEP SOUND | 16 | PRESS MENU FOR >5 SECS | | DISABLES BEEPER |
| ACTIVATE HAND REMOTE<br><br>CHANGE DEVICE ID | -<br><br>39 | <br><br>DISPLAY | AIM REMOTE AT DVR<br><br>CHANGE ID | PRESS DEV KEY, 88 AND ENTER ON REMOTE<br><br>AS ABOVE – REPLACE ID |
| MAIN/SPOT MONITOR OUTPUT | 34/35 | DISPLAY | PREVIEW<br>SELECT OUT | SELECT MAIN OR SPOT<br>CONFIRM CHANGES<br>DISPLAY MENU<br>CONFIRM |
| COVERT CAMERA<br>ADD NEW USER/PSWD<br><br>LOG ON TO NEW USER | 37<br><br><br>49 | PRESS MENU<br><br><br>DISPLAY | <br>ADD USER<br><br>PREVIEW | <br>SET RIGHTS & REBOOT<br><br>INPUT 0 TO CHANNEL |

This CCTV installation tip is aimed at helping you to install CCTV equipment. If you are looking for answers on "how to fit CCTV" or perhaps "how to network a DVR or NVR" or even "how to get CCTV on your mobile phone" why not check out our full range of CCTV installation tips at: **www.systemq.com**

***How to guides aim to answer commonly asked questions in a concise and informative manner. They are for advice & guidance only and do not replace any of the manuals or other literature supplied with our products.***

System Q Ltd. McGregor's Way, Turnoaks Business Park, Hasland, Chesterfield, S40 2WB
Telephone: **01246 200 000** Website: **www.systemq.com** Email: **support@systemq.com**

Copyright © System Q ltd